

# XONE 42





The Xone:42 is a new, compact 4-channel DJ mixer with USB audio interface, designed for DJ's of all abilities and experience from top pro DJ's to bedroom enthusiasts who want a compact quality mixer with pro features.

Integral to the mixer's design is a new feature - the 'X-FX' control - allowing signal to be sent to external FX, and returned to be combined with the now legendary Xone VCF filter system.

There's even a USB port which allows easy connection to a computer and integration of digital media, which can be used to play back music files from a laptop and to record mixes, or used with software as a digital DJ effects unit.

The Xone:42 is so neat and packed with useful features that it'll find a home in any bar, club or even your bedroom!



<b>XONE:42</b>	Desk mount	Rack ears(1)	Rack ears (2)	Packed
mm(") <b>Width</b>	305 (12)	355 (14)	483 (19)	490 (19.5)
mm(") <b>Height</b>	84 (3.3)	84 (3.3)	84 (3.3)	205 (8.1)
mm(") <b>Depth</b>	358 (14)	358 (14)	358 (14)	450 (17.7)
kg(lb) <b>Weight</b>	5 kg (11)			7 (15.4)

## FEATURE LIST

### 4 dual stereo channels

Channels 1 & 4 have phono (RCA RIAA turntable) inputs or TRS jack line, while channels 2 and 3 are line/line

### 3 band EQ

All channels have +6dB to total kill EQ

### X-FX send to external FX

Allows signal to be sent to external FX, and returned to be combined with VCF controls

### VCF filter

Stereo filter with independent in/out, resonance & frequency controls

### VCA Crossfader

with curve control from sharp attack for scratching to smooth attack for house style

### USB 1.1 port

One stereo up to PC and one stereo back

### Microphone input

On XLR, with 2-band EQ and level control

### 2 headphone outputs

1/4" and 3.5mm

### Power supply

High performance internal switch-mode psu

### Rack ears

Optional rack ears available

